

サーボフレックスカップリング 切り替え資料

SFC-S ⇒ SFC-SA2

型式	型式	許容トルク	外径	全長
SFC-S	SFC-SA2	[N・m]	[mm]	[mm]
-	SFC-005SA2	0.5	16	16.7
-	SFC-010SA2	0.8	19	19.35
-	SFC-020SA2	1.5	26	23.15
-	SFC-030SA2	4	34	27.3
SFC-03S	-	3	34	27
-	SFC-035SA2	6	39	34
-	SFC-040SA2	10	44	34
SFC-04S	-	6	44	34
-	SFC-050SA2	25	56	43.4
SFC-05S	-	12	56	45
-	SFC-060SA2	60	68	53.6

SFC-WP/WA ⇒ SFC-DA2

型式	型式	許容トルク	外径	全長
SFC-WP/WA	SFC-DA2	[N・m]	[mm]	[mm]
-	SFC-005DA2	0.5	16	23.2
-	SFC-010DA2	0.8	19	25.9
-	SFC-020DA2	1.5	26	32.3
-	SFC-030DA2	4	34	37.8
SFC-03WP	-	3	34	37
-	SFC-035DA2	6	39	48
-	SFC-040DA2	10	44	48
SFC-04WP	-	6	44	47
-	SFC-050DA2	25	56	59.8
SFC-05WP	-	12	56	61
-	SFC-060DA2	60	68	73.3
SFC-06WA	-	40	68	74

SFC-SD ⇒ SFC-SA2

型式	型式	許容トルク	外径	全長
SFC-SD	SFC-SA2	[N・m]	[mm]	[mm]
-	SFC-005SA2	0.5	16	16.7
-	SFC-010SA2	0.8	19	19.35
SFC-010SD	-	1	19	19.9
-	SFC-020SA2	1.5	26	23.15
SFC-020SD	-	1.5	26	23.5
-	SFC-030SA2	4	34	27.3
SFC-030SD	-	3	34	27.1
-	SFC-035SA2	6	39	34
SFC-035SD	-	6	39	34.1
-	SFC-040SA2	10	44	34
SFC-040SD	-	9	44	34.1
-	SFC-050SA2	25	56	43.4
SFC-050SD	-	25	56	45
-	SFC-060SA2	60	68	53.6
SFC-060SD	-	60	68	54
SFC-080SD	-	100	82	68

SFC-WD ⇒ SFC-DA2

型式	型式	許容トルク	外径	全長
SFC-WD	SFC-DA2	[N・m]	[mm]	[mm]
-	SFC-005DA2	0.5	16	23.2
-	SFC-010DA2	0.8	19	25.9
SFC-010WD	-	1	19	26.7
-	SFC-020DA2	1.5	26	32.3
SFC-020WD	-	1.5	26	31.9
-	SFC-030DA2	4	34	37.8
SFC-030WD	-	3	34	37.2
-	SFC-035DA2	6	39	48
SFC-035WD	-	6	39	47.2
-	SFC-040DA2	10	44	48
SFC-040WD	-	9	44	47.2
-	SFC-050DA2	25	56	59.8
SFC-050WD	-	25	56	61
-	SFC-060DA2	60	68	73.3
SFC-060WD	-	60	68	74
SFC-080WD	-	100	82	98